

P1: The Main GPIO connector							
WiringPi Pin	BCM GPIO	Name	Header		Name	BCM GPIO	WiringPi Pin
		3.3v	1	2	5v		
8	Rv1:0 - Rv2:2	SDA	3	4	5v		
9	Rv1:1 - Rv2:3	SCL	5	6	0v		
7	4	GPIO7	7	8	TxD	14	15
		0v	9	10	RxD	15	16
0	17	GPIO0	11	12	GPIO1	18	1
2	Rv1:21 - Rv2:27	GPIO2	13	14	0v		
3	22	GPIO3	15	16	GPIO4	23	4
		3.3v	17	18	GPIO5	24	5
12	10	MOSI	19	20	0v		
13	9	MISO	21	22	GPIO6	25	6
14	11	SCLK	23	24	CE0	8	10
		0v	25	26	CE1	7	11
WiringPi Pin	BCM GPIO	Name	Header		Name	BCM GPIO	WiringPi Pin

